

IC-GM1600



GMDSS Portable for Survival Craft

- **Meets the strict environmental requirements for survival craft radio**

The IC-GM1600 meets temperature, thermal shock, vibration and drop resistant (from 1 m height) requirements. After passed those environmental tests, the IC-GM1600 sustains 1m depth waterproof construction specified with IMO resolutions A.809(19), A.694(17) and IEC 61097-12.

- **Optional high capacity Lithium battery, BP-234, has superior low temperature characteristics**

Provides more than 8 hours operating time even at -20°C (Duty cycle: Tx: Rx: Stand-by = 6: 6: 48)

- **Large keypad with positive button action**

- **Wide viewing angle LCD display**

- **"Speed water removal" system removes water from the speaker grill**

- **Other features**

- One touch access to Channel 16 and call channel
- Highly visible yellow colored body
- Bright LED indicator on the top of panel
- Optional VOX headset for on-board use



SPECIFICATIONS

GENERAL

- Frequency range Tx/Rx : 156.300–156.875MHz
- Mode : FM (16K0G3E)
- Power supply requirement : 7.5/7.2V DC nominal
- Current drain (approx. at 7.5/7.2V DC) :
 - Tx 2W output 1.0A
 - 1W output 0.7A
 - Rx AF max. 200mA
- Operating Temp. range :
 - USA version –20°C to +60°C ; –4°F to +140°F
 - General version –20°C to +55°C
- Antenna impedance : 50Ω (SMA fixed-type)
- Dimensions (W×H×D) : 65×145×44 mm; (projections not included) 2⁹/₁₆×5²³/₃₂×1²³/₃₂ in
- Weight (approx.) : 385g; 13.6oz (with BP-234)

Measurement made in accordance with TIA/EIA-603 and FCC part 80.271 for USA version. All stated specifications are subject to change without notice or obligation.

TRANSMITTER

- Output power : 2W/1W (Hi/Low)
- Max. frequency deviation : ± 5.0kHz
- Frequency error :
 - USA version ± 5.0ppm
 - General version ± 1.5kHz
- Spurious emissions :
 - USA version –70dBc typ.
 - General version 0.25μW (30MHz–1GHz)
1.00μW (1GHz–2GHz)
- Adjacent channel power : 70dB
- FM Hum and noise ratio : 40dB
- Audio harmonic distortion : Less than 10% (at 60% mod.)

- Supplied accessories:** (* Depending on version)
- Battery pack, BP-224
 - Battery charger, BC-158
 - AC adapter, BC-147A/E*
 - Belt clip, MB-103Y
 - Antenna, FA-S61V
 - Hand strap

RECEIVER

- Sensitivity :
 - USA version 0.25μV typ. (12dB SINAD)
 - General version –2dBμ typ. (emf: 20dB SINAD)
- Squelch sensitivity :
 - USA version 0.35μV typ. (at threshold)
 - General version 0dBμ typ. (emf: at threshold)
- Adjacent channel selectivity :
 - USA version 70dB typ.
 - General version 70dB
- Spurious response :
 - USA version 70dB typ.
 - General version 70dB
- Intermodulation rejection :
 - USA version 70dB typ.
 - General version 68dB
- Hum and noise ratio : 40dB
- Audio output power (at 10% distortion with an 8Ω load) :
 - USA version 0.35W typ.
 - General version 0.2W

OPTIONS

BATTERY PACKS



<For survival craft>
BP-234 9.0V/3300mAh LITHIUM BATTERY PACK
 Large capacity non-rechargeable battery pack.

<For on-board use>
BP-224/BP-225 Ni-Cd BATTERY PACKS
 BP-224 : 7.2V/750mAh. Same as supplied.
 BP-225 : 7.2V/1100mAh.

REGULAR CHARGER



<For on-board use>
BC-158 DESKTOP CHARGER
 + **BC-147A/E** AC ADAPTER
 Regularly charges the BP-224 in 8–12 hours and the BP-225 in 12–18 hours. Same as supplied.

RAPID CHARGER



<For on-board use>
BC-119N DESKTOP CHARGER
 + **AD-109** CHARGER ADAPTER
 + **BC-145A/E** AC ADAPTER
 For rapid charging of battery pack. Charges the BP-224 1.5–2.0 hours and the BP-225 2.2–2.8 hours.

MULTI CHARGER



<For on-board use>
BC-121N MULTI-CHARGER + **AD-109** CHARGER ADAPTER
 + **BC-124** AC ADAPTER
 For rapid charging of up to 6 BP-224 battery packs (Six AD-109s are required). Charges the BP-224 in 1.5–2.0 hours the BP-225 2.2–2.8 hours.

HEADSETS and ADAPTER CABLE



<For on-board use>
HS-94 EARPHONE-HEAD HEADSET
HS-95 BEHIND-THE-HEAD HEADSET
HS-97 THROAT MICROPHONE
 + **OPC-1392** HEADSET ADAPTER CABLE
 For VOX hands-free operation. These headsets are not waterproof.

SPEAKER-MICROPHONE



<For on-board use>
HM-125
 Full sized, submersible construction corresponds to IPX7 (1 m depth /30 min.).

BELT CLIPS



MB-103Y : Alligator type belt clip. Same as supplied.
MB-86 : Swivel belt clip. Prevents accidental dropping from your belt.

LEATHER BELT HANGERS



MB-96F : Fixed type belt hanger. Use with MB-103Y.
MB-96N : Swivel type belt hanger. Swivel joint of the MB-86 is supplied.

<For on-board use>
POWER SUPPLY CABLES
CP-17L CIGARETTE LIGHTER CABLE WITH NOISE FILTER
OPC-515L DC POWER CABLE
 For use with the BC-119N with an external DC power supply. (12–16 V DC required)
OPC-656 DC POWER CABLE
 For use with the BC-121N with a DC power supply. (12–16V DC required)

Icom Inc.

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
 Bellevue, WA 98004, U.S.A.
 Phone: +1 (425) 454-8155
 Fax: +1 (425) 454-1509
 E-mail: sales@icomamerica.com
 URL: <http://www.icomamerica.com>

Icom Canada

Glenwood Centre #150-6165 Highway 17,
 Delta, B.C., V4K 5B8, Canada
 Phone: +1 (604) 952-4266
 Fax: +1 (604) 952-0090
 E-mail: info@icomcanada.com
 URL: <http://www.icomcanada.com>

Icom (Australia) Pty. Ltd.

A.B.N. 88 006 092 575
 290-294 Albert Street, Brunswick,
 Victoria, 3056, Australia
 Phone: +61 (03) 9387 0666
 Fax: +61 (03) 9387 0022
 E-mail: sales@icom.net.au
 URL: <http://www.icom.net.au>

Icom New Zealand

146A Harris Road, East Tamaki,
 Auckland, New Zealand
 Phone: +64 (09) 274 4062
 Fax: +64 (09) 274 4708
 E-mail: inquiries@icom.co.nz
 URL: <http://www.icom.co.nz>

Icom (Europe) GmbH

Communication Equipment
 Himmelgeister Str. 100,
 D-40225 Düsseldorf, Germany
 Phone: +49 (0211) 346047
 Fax: +49 (0211) 333639
 E-mail: info@icom.eu
 URL: <http://www.icomeurope.com>

Icom Spain S.L.

Ctra. de Gracia a Manresa Km. 14.750
 08190 Sant Cugat del Valles Barcelona, Spain
 Phone: +34 (93) 590 26 70
 Fax: +34 (93) 589 04 46
 E-mail: icom@icomspain.com
 URL: <http://www.icomspain.com>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
 Kent, CT6 8LD, U.K.
 Phone: +44 (01227) 741741
 Fax: +44 (01227) 741742
 E-mail: info@icomuk.co.uk
 URL: <http://www.icomuk.co.uk>

Icom France S.a

Zac de la Plaine, 1,
 Rue Brindejonc des Moulinais BP 5804,
 31505 Toulouse Cedex, France
 Phone: +33 (5) 61 36 03 03
 Fax: +33 (5) 61 36 03 00
 E-mail: icom@icom-france.com
 URL: <http://www.icom-france.com>

Icom Polska

Sopot, 3 maja 54, Poland
 Phone: +48 (58) 550 7135
 Fax: +48 (58) 551 0484
 E-mail: icompolksa@icompolksa.com.pl
 URL: <http://www.icompolksa.com.pl>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
 Taipei, Taiwan, R.O.C.
 Phone: +886 (02) 2559 1899
 Fax: +886 (02) 2559 1874
 E-mail: sales@asia-icom.com
 URL: <http://www.asia-icom.com>

Beijing Icom Ltd.

1305, Wanshang Plaza, Shijingshan Road,
 Beijing, China
 Phone: +86 (010) 6866 6337
 Fax: +86 (010) 6866 3553
 E-mail: bjicom@bjicom.com
 URL: <http://www.bjicom.com>



Icom Inc. (Japan), is an ISO 9001 and ISO 14001 certification acquired company.

Your local distributor/dealer: